



- ① RAIN BIRD CONTROLLER
- ② SOLID BARE COPPER WIRE (#10 AWG) FROM GROUNDING ROD TO CONTROLLER. MAKE WIRE AS SHORT AND STRAIGHT AS POSSIBLE
- ③ COVER GROUNDING ROD WITH 10-INCH ROUND VALVE BOX AS SHOWN
- ④ 5/8-INCH X 8 FT COPPER CLAD GROUNDING ROD OR GROUNDING PLATE. INSTALL RODS IN SOIL IN A TRIANGULAR PATTERN SPACED A MINIMUM OF 16 FT APART FROM EACH OTHER. GROUNDING GRID TO HAVE A RESISTANCE OF TEN (10) OHMS OR LESS
- ⑤ BARE COPPER WIRE (#10 AWG MIN.) BETWEEN GROUNDING RODS
- ⑥ GROUND ROD CLAMP OR WELDS
- ⑦ FINISH GRADE

D

**CONTROLLER GROUNDING GRID**  
 N.T.S. **Y DESIGN LAYOUT**

6-15-10